

User Manual



XMP Series

6U High Resolution Monitor Panel

1920 x 1200
WUXGA

Options Available:

- SDI / MCS
- DC Power
- Touch-Screen
- MIL-Type or Lockable Connector

FC CE

Designed/Manufactured by Austin Hughes and Distributed by Eclipse Rackmount, Inc.

Legal Information

First English printing, October 2002

Information in this document has been carefully checked for accuracy; however, no guarantee is given to the correctness of the contents. The information in this document is subject to change without notice. We are not liable for any injury or loss that results from the use of this equipment.

Safety Instructions

Please read all of these instructions carefully before you use the device. Save this manual for future reference.

- Unplug equipment before cleaning. Don't use liquid or spray detergent; use a moist cloth.
- Keep equipment away from excessive humidity and heat. Preferably, keep it in an air-conditioned environment with temperatures not exceeding 40° Celsius (104° Fahrenheit).
- When installing, place the equipment on a sturdy, level surface to prevent it from accidentally falling and causing damage to other equipment or injury to persons nearby.
- When the equipment is in an open position, do not cover, block or in any way obstruct the gap between it and the power supply. Proper air convection is necessary to keep it from overheating.
- Arrange the equipment's power cord in such a way that others won't trip or fall over it.
- If you are using a power cord that didn't ship with the equipment, ensure that it is rated for the voltage and current labeled on the equipment's electrical ratings label. The voltage rating on the cord should be higher than the one listed on the equipment's ratings label.
- Observe all precautions and warnings attached to the equipment.
- If you don't intend on using the equipment for a long time, disconnect it from the power outlet to prevent being damaged by transient over-voltage.
- Keep all liquids away from the equipment to minimize the risk of accidental spillage. Liquid spilled on to the power supply or on other hardware may cause damage, fire or electrical shock.
- Only qualified service personnel should open the chassis. Opening it yourself could damage the equipment and invalidate its warranty.
- If any part of the equipment becomes damaged or stops functioning, have it checked by qualified service personnel.

What the warranty does not cover

- Any product, on which the serial number has been defaced, modified or removed.
- Damage, deterioration or malfunction resulting from:
 - Accident, misuse, neglect, fire, water, lightning, or other acts of nature, unauthorized product modification, or failure to follow instructions supplied with the product.
 - Repair or attempted repair by anyone not authorized by us.
 - Any damage of the product due to shipment.
 - Removal or installation of the product.
 - Causes external to the product, such as electric power fluctuation or failure.
 - Use of supplies or parts not meeting our specifications.
 - Normal wear and tear.
 - Any other causes which does not relate to a product defect.
- Removal, installation, and set-up service charges.

Regulatory Notices Federal Communications Commission (FCC)

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

Any changes or modifications made to this equipment may void the user's authority to operate this equipment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Re-position or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Contents

< Part. 1 > XMP-17

| | | |
|-----|--------------------------------|---------|
| 1.1 | Package Contents | P.1 |
| 1.2 | Structure Diagram & Dimensions | P.1 - 2 |
| 1.3 | Installation | P.3 |

< Part. 2 > Specifications / OSD / Remote Controller

| | | |
|-----|---|---------|
| 2.1 | Product Specifications | P.4 - 5 |
| 2.2 | On-Screen Display Operation (OSD) | P.6 - 7 |
| 2.3 | Picture In Picture (PIP) / Picture By Picture (PBP) | P.8 - 9 |

< Part. 3 > Options

| | | |
|-----|--|------|
| 3.1 | 3G / HD / SD- SDI Broadcast-grade input | P.10 |
| 3.2 | MCS Multi-Display Control Solution | P.11 |
| 3.3 | 17" Touch-Screen : Resistive, Capacitive | P.12 |
| 3.5 | 48V, 24V or 12VDC power | P.13 |
| 3.6 | MIL-Type or Lockable Connector | P.14 |

Before Installation

- It is very important to mount the equipment in a suitable cabinet or on a stable surface.
- Make sure the place has a good ventilation, is out of direct sunlight, away from sources of excessive dust, dirt, heat, water, moisture and vibration.

Unpacking

The equipment comes with the standard parts shown in package content. Check and make sure they are included and in good condition. If anything is missing, or damaged, contact the supplier immediately.

How To Clean Your LCD Monitor



Caution :

- To avoid the risk of electric shock, make sure your hands are dry before unplugging your monitor from or plugging your monitor into an electrical outlet.
- When you clean your monitor, do not press down on the LCD screen. Pressing down on the screen can scratch or damage your display. Pressure damage is not covered under warranty.
- Use only cleansers made specifically for cleaning monitors and monitor screens. Cleansers not made to clean monitors and monitor screens can scratch the LCD display or strip off the finish.
- Do not spray any kind of liquid directly onto the screen or case of your monitor. Spraying liquids directly onto the screen or case can cause damage which is not covered under warranty.
- Do not use paper towels or abrasive pads to clean your monitor. Using an abrasive pad or any wood based paper product such as paper towels can scratch your LCD screen.

Cleaning Your Monitor

To clean your LCD safely, please follow these steps :

- ① Disconnect the power cord.
- ② Gently wipe the surface using a clean, dry microfiber cloth. Use as little pressure as possible.

Cleaning Tough Marks and Smudges

To remove tough marks and smudges, please follow these steps :

- ① Disconnect the power cord.
- ② Spray a small amount of non-abrasive cleanser on a microfiber cloth.



Caution : Do not spray or apply any liquids directly onto the monitor. Always apply the solution to your microfiber cloth first, not directly on the parts you are cleaning.

- ③ Gently wipe the surface. Use as little pressure as possible.
- ④ Wait until your monitor is completely dry before plugging it in and powering it up.

< Part 1 >

< 1.1 > Package Contents


XMP-17



XMP-17 unit X 1


- 6ft VGA cable X 1
- Power adapter X 1
- Power cord X 1

< 1.2 > Structure Diagram




< 1.2 > Dimensions


Front View



Side View




Bottom View




UNIT : mm
1mm = 0.03937 inch

| Model | Product Dimension (W x D x H) | Packing Dimension (W x D x H) | Net Weight | Gross Weight |
|---------------|---|--|-------------------|--------------------|
| XMP-17 | 480 x 48 x 266 mm 18.9 x 1.9 x 10.5 inch | 529 x 124 x 451 mm 20.8 x 4.9 x 17.8 inch | 4.2 kg 9.2 lbs | 6.2 kg 13.6 lbs |



Step 1

- Mount the display panel with M6 screw set.
 - M6 screw x 4 pcs required (Left & right side).
- M6 screw sets are not provided.**



Step 2

- Fix the LCD into the rack.

< Part 2 >

< 2.1 > Product Specifications

| | | |
|------------------|--------------------------------|------------------------------------|
| LCD Panel | Panel Size (diagonal) | 17.1-inch Widescreen TFT color LCD |
| | Display pixel (dots x lines) | 1920 x 1200 |
| | Brightness (typ.) | 210 |
| | Contrast Ratio (typ.) | 600:1 |
| | Color | 16.7 M, 8-bit |
| | Viewing Angle (L/R/U/D) | 65/65/55/55 |
| | Response Time (ms) | 30 |
| | Dot pitch (mm) | 0.191 |
| | Display Area (mm) | 367.20H x 229.50V |
| | Surface treatment | Anti-glare, Hard-coating |
| | Surface hardness | 3H |
| | Backlight Type | LED |
| | MTBF (hrs) | 20,000 |

| | | | |
|---------------------------|-----------------|-------------------|---------------------------|
| Video Connectivity | Digital | HDMI | HDMI 1.1, CEA-861-D |
| | | DVI | DVI-D, TMDS single link |
| | Analog | VGA | Analog 0.7Vp-p |
| | | Composite (BNC) | NTSC & PAL |
| | | S-Video (4-pin) | NTSC & PAL |
| | Plug & Play | DVI / VGA | VESA EDID structure 1.3 |
| | Synchronization | VGA | Separate, Composite & SOG |

| | | | |
|---------------------------|--------------|--------------------------|-------------------|
| Audio Connectivity | Audio Input | Connector | 3.5mm stereo jack |
| | | Impedance / Power level | 30kΩ / 750mV |
| | Audio Output | Connector | 3.5mm stereo jack |
| | | Resistance / Power level | 30kΩ / 2.8V |
| | | Speaker Output | Power |

*When the audio output is connected, speaker output is OFF

| | | | |
|--------------|-------------------|-------------------|---------------------------------------|
| Power | Power Supply | Range | Auto-sensing 100 to 240VAC, 50 / 60Hz |
| | Power Consumption | Screen display ON | 34W or less |
| | | Power saving mode | 4W or less |
| | | Power button OFF | 1W or less |








| | | |
|-------------------|-----------------|----------|
| Regulatory | Safety Approval | FCC & CE |
|-------------------|-----------------|----------|


| | | | |
|---------------------------------|-----------------------|-------------|----------------------------------|
| Environmental Conditions | Operating | Temperature | 0 to 50°C degree |
| | | Humidity | 20~90%, non-condensing |
| | Storage | Temperature | -5 to 60°C degree |
| | | Humidity | 5~90%, non-condensing |
| | | Shock | 10G acceleration (11ms duration) |
| Vibration | 5~500Hz 1G RMS random | | |



| | | |
|-------------------------------|-----------------------|--|
| Physical Specification | Product (W x D x H) | 480 x 48 x 266 mm 18.9 x 1.9 x 10.5 inch |
| | Packing (W x D x H) | 529 x 124 x 451 mm 20.8 x 4.9 x 17.8 inch |
| | Net Weight | 4.2 kgs / 9.2 lbs |
| | Gross Weight | 6.2 kgs / 13.6 lbs |

| | | | |
|--------------------------|-------------------|---------------------------------------|-----------------------------|
| Applicable Format | DVI-D / VGA Input | PC Signal | 1920 x 1200 x 60Hz |
| | | | 1360 x 768 x 60Hz |
| | | | 1280 x 1024 x 60 / 75Hz |
| | | | 1280 x 960 x 60Hz |
| | | | 1280 x 768 x 60 / 75Hz |
| | | | 1152 x 864 x 75Hz |
| | | | 1024 x 768 x 60 / 70 / 75Hz |
| | | | 848 x 480 x 60Hz |
| | | | 800 x 600 x 60 / 72 / 75Hz |
| | | | 720 x 400 x 70Hz |
| | | | 640 x 480 x 60 / 72 / 75Hz |
| | 640 x 400 x 70Hz | | |
| | 640 x 350 x 70Hz | | |
| | HDMI Input | PC Signal | Same as VGA |
| Video Signal | | | 1080p : 60Hz |
| Audio Signal | | 720p : 50 / 60Hz | |
| | | 480p : 60Hz | |
| | | 576p : 50Hz | |
| | | 2ch Linear PCM (32 / 44.1 / 48 KHz) | |

< 2.2 > On-Screen Display Operation (OSD)


| Membrane Switch | Function |
|---|--|
|  | Turn the monitor on or off |
|  | Display the OSD menu Act as an Enter key to select screen setting options |
|     | Scroll through menu options and adjust the displayed control |
|  | Exit the OSD screen Go back to the previous on-screen sub-menu or main menu |

Remark : All LED touch buttons in **WHITE** light.
The LED of **Power**  touch button will flash continuously when there is no signal input.

- ① All the LED touch buttons will automatically turn off after 10 minutes of idle status (except the **Power** ).
- ② Light up all membrane buttons, please press any button for 1 - 2 seconds (except the **Power** ).

① Picture

- Picture mode : Standard / Vivid / Soft / User mode to choose
- Brightness : Adjust background black level of the screen image
- Contrast : Adjust the difference between the image background (black level) and the foreground (white level)
- Hue: Adjust the screen hue value
- Saturation : Adjust the saturation of the image color
- Picture size : Adjust the image size
- Color temp : Standard / Cool / Warm / User to choose
- Noise reduce : Reduce the noise of the image
- Sharpness : Adjust the image from weak to sharp




Picture

- Picture mode
- Brightness
- Contrast
- Hue
- Saturation
- Picture size
- Color temp
- Noise reduce
- Sharpness


② PC

- Auto adjust : Automatically adjust sizes, centers and fine tunes the video signal to eliminate waviness and distortion.
- Clock : Adjust the clock value
- Phase : Adjust the phase value
- H. Position : Align the screen image left or right
- V. Position : Align the screen image up or down




③ Audio

- Audio mode : Movie / Voice / Normal / Music mode to choose
- Volume : Adjust the volume of sound
- Bass : Set the value of bass sound
- Treble : Set the value of treble sound
- Balance : Set the balance value of treble and bass sound
- Analog TV audio : Set the value of analog TV audio sound
- Mute : Turn off the surrounding sound



④ MISC

- Language : Select the language in which the OSD menu is displayed - English
- Sleep timer : Set the off time
- PIP mode : Adjust picture in picture setting
- PIP position : Enter into PIP position
- PIP source : Enter into the Sub source and sound source
- System reset : Return the adjustment back to factory setting
- Information : Select for Help




< 2.3 > How to Use Picture In Picture (PIP) / Picture By Picture (PBP)

< 2.3.1 > Picture in Picture (PIP)

Mode

Display the Sub screen in the Main screen.


OSD Menu → MISC → PIP Mode → Large / Small / OFF




Position

Adjust the position of the Sub screen (top left, bottom left, top right, bottom right)


OSD Menu → MISC → PIP Position → top left / top right / bottom left / bottom right




top left



top right



bottom left



bottom right

Size

Adjust the size of the Sub screen (Large / Small)

OSD Menu → MISC → PIP Mode → Large / Small

Size of Sub screen

| LCD Monitor | Large Sub screen | Small Sub screen |
|-------------|------------------|------------------|
| 1920 x 1200 | 552 x 414 | 480 x 360 |
| 1920 x 1080 | 552 x 414 | 480 x 360 |
| 1440 x 900 | 414 x 310 | 360 x 270 |
| 1366 x 768 | 392 x 294 | 340 x 254 |
| 1280 x 1024 | 368 x 276 | 320 x 240 |

< 2.3.2 > Picture By Picture (PBP)

Mode

Display the Sub screen next to the Main screen.

OSD Menu → MISC → PIP Mode → PBP



Size

| LCD Monitor | Main / Sub screen |
|-------------|-------------------|
| 1920 x 1200 | 955 x 716 |
| 1920 x 1080 | 955 x 716 |
| 1440 x 900 | 715 x 536 |
| 1366 x 768 | 678 x 508 |
| 1280 x 1024 | 635 x 476 |

< 2.3.3 > PIP / PBP Source

To select an input signal for PIP / PBP Sub screen.

OSD Menu → MISC → PIP Source → VGA / S-Video / Composite / DVI / HDMI / SDI / YPbPr / TV

The PIP / PBP is operable in the following table :

| Main \ Sub | VGA | S-Video | Composite | DVI-D | HDMI | SDI | YPbPr | TV |
|------------|-----|---------|-----------|-------|------|-----|-------|----|
| VGA | X | O | O | O | O | O | O | O |
| S-Video | O | X | X | O | O | O | O | X |
| Composite | O | X | X | O | O | O | O | X |
| DVI | O | O | O | X | X | O | O | O |
| HDMI | O | O | O | X | X | O | O | O |
| SDI | O | O | O | O | O | X | X | O |
| YPbPr | O | O | O | O | O | X | X | O |
| TV | O | X | X | O | O | O | O | X |

< Part 3 >


< 3.1 > Options : 3G / HD / SD-SDI input



The SDI input is an ideal solution for the broadcast-grade video and high resolution CCTV market.

Designed for use with CyberV iew Full HD 1080p and ultra high resolution 1920 x 1200 LCD displays , the board provides a SDI input module without using additional space or power and it comes standard with a 2-year warranty.

SDI



| | | |
|--------------|------------|--|
| INPUT | 3G-SDI IN | BNC x 1 / 0.8Vp-p (75 ohm) |
| | 3G-SDI OUT | BNC x 1 / Active through, equalized & relocked |

| | | |
|----------------------------|-------|---|
| Standard Compliance | Video | SMPTE 425M / 274M / 296M / 125M ITU-R BT.656 |
| | Audio | SMPTE 299M / 272M-C |

| | | |
|--------------------------------|-------------------|------------------------------|
| Compatible Video Format | 3G-SDI | 1080p @60 / 50Hz, 4:2:2 |
| | | 1080p @30 / 25 / 24Hz, 4:4:4 |
| | | 1080i @60 / 50Hz, 4:4:4 |
| | | 720p @60 / 50Hz, 4:4:4 |
| | HD-SDI | 1080p @30 / 25 / 24Hz, 4:2:2 |
| 1080i @60 / 50Hz, 4:2:2 | | |
| 720p @60 / 50Hz, 4:2:2 | | |
| SD-SDI | 480i @60Hz, 4:2:2 | |
| ITU-R BT.656 | 576i @50Hz, 4:2:2 | |

| | | |
|--------------------------------|--------|---|
| Compatible Audio Format | 3G-SDI | 48kHz, 16 / 20 / 24 bit, 2 CH, Synchronized Video |
| | HD-SDI | 48kHz, 16 / 20 / 24 bit, 2 CH, Synchronized Video |
| | SD-SDI | 48kHz, 16 / 20 / 24 bit, 2 CH, Synchronized / Asynchronized Video |

| | | |
|--|--------|-------------------|
| Max. Transmission Distance 75 ohm coaxial cable | 3G-SDI | 150m at 2.97Gb/s |
| | HD-SDI | 250m at 1.485Gb/s |
| | SD-SDI | 480m at 270Mb/s |

< 3.2 > Options : MCS (Multi-Display Control)


XMP-17



The MCS solution is able to control the OSD of various CyberView LCD displays up to 64 units.


The RS-232C is used for the communication between the PC and first display via a 15' serial cable, while the CAN bus is used for the LCD displays. They may be cascaded together via Cat 5/6 and daisy chained up to 1,000 meters.

Specifically designed for our displays, the MCS input module saves additional space/power and is covered by the 2-year standard warranty.



*** For additional information and specs on MCS, please contact your supplier.

*** For the MCS option, casing depth will be changed.




< 3.2 > Options : Touch-Screen & Driver

17" USB Touch-Screen Specification

| Model | TRB e-Resistive | TCB e-Capacitive |
|-----------------------|-------------------------------|---------------------|
| Technology | 5-Wire Resistive | Capacitive |
| Touch Point | Single | Single |
| Method | Stylus or Finger | Finger |
| Activation Force | ≤ 50g / Stylus=R0.8 | ≤ 50g |
| Durability | 10 million touches | 300 million touches |
| Response Time | 15 ms | 20 ms |
| Optical Transmittance | 80% ± 3% | 92% ±2% |
| Surface Hardness | 3H | 9H |
| Haze | 8% ± 3% | 7% |
| Glass | 2.2 ±0.2 mm | 2.8 mm ±10% |
| Connector | USB Type A | |
| Compatibility | Windows 7 / XP / Vista, Linux | |

- USB touch-screen package includes 1 x 6ft USB cable, quick reference guideline and CD disc
- For detailed information, please refer to the attached CD disc
- As the touch-screen unit is not made of toughened glass, please handle it carefully

USB Touch-Screen




TRB & TCB Driver


Please follow the below steps to setup the touch-screen:

- Step 1.** Run the bundled CD disc or download the driver from the link below :
<http://www.austin-hughes.com/downloads/RMDL/software.html>
- Step 2.** Double click the Setup.exe
- Step 3.** Follow the installation instruction to finish the setup
- Step 4.** After installation, run the TouchKit program & the “4 point calibration”



Please do the initial calibration after the first setup







| Model | 12V | 24V | 48V |
|----------------------|---------|----------|----------|
| Input rating | | | |
| Input voltage: | 12-Volt | 24-Volt | 48-Volt |
| Input range: | 9 ~ 18V | 18 ~ 36V | 36 ~ 75V |
| Input current | | | |
| - No load | 50 mA | 50 mA | 50 mA |
| - Full load | 4950 mA | 2450 mA | 1220 mA |
| Output rating | | | |
| Output voltage: | 12-Volt | 12-Volt | 12-Volt |
| Output current: | 4.16A | 4.16A | 4.16A |
| Efficiency | 84% | 85% | 85% |

< 3.4 > Options : MIL-Type or Lockable Connector

| | Input | Part no. | MIL Standard |
|-----------------------------|--------------------------|---|-------------------|
| MIL - Type Connector | DC Power *** (Male) | MS3470W8-33P  | MIL - DTL - 26482 |
| | VGA *** (Male) | MS3470W14-15P  | MIL - DTL - 26482 |

*** There are several additional MIL DC and VGA connector types with varying design characteristics to meet cost considerations and to provide users with the most design flexibility possible. For more information, please contact your supplier.

| | Input | Part no. | Standard |
|---------------------------|----------------------|--|------------|
| Lockable Connector | DC Power (Male) | YM-Ext-461CP001  | D-type 3W3 |
| | USB | LUSB - A111 - 00  | - |

*** MIL - Type or lockable connectors above can be integrated with our LCD displays. Connectors are not available independently.

The company reserves the right to modify product specifications without prior notice and assumes no responsibility for any error which may appear in this publication.

All brand names, logo and registered trademarks are properties of their respective owners.

Copyright 2013 Austin Hughes Electronics Ltd. & Eclipse Rackmount, Inc. All rights reserved.